

VF 1000 S.No. 96-40-38

Test Results

Signal to Noise Ratio: measured peak wideband

Left	-101dB
Right	-101dB

Harmonic Distortion: 1kHz at full output

Harmonic	Left		Right	
2kHz	-65dB	0.05%	-66dB	0.05%
3kHz	-78dB	0.01%	-78dB	0.01%
4kHz	-84dB	0.006%	-86dB	0.005%
5kHz	-90dB	0.003%	-90dB	0.003%

Harmonics above 5kHz are beyond the limits of my test equipment.

Frequency response at full output ref 1kHz

Frequency	Left Output	Right Output
4Hz	-3.0	-3.0
5Hz	-2.0	-2.0
7Hz	-1.1	-1.1
10Hz	-0.6	-0.6
15Hz	-0.4	-0.4
20Hz	-0.3	-0.3
30Hz	-0.1	-0.1
100Hz	-0.05	0
300	0	0
1kHz	0	0
3kHz	0	0
7kHz	-0.1	-0.1
10kHz	-0.3	-0.3
20kHz	-1.0	-1.1
30kHz	-2.1	-2.1
36kHz	-3.0	-3.0
57kHz	-6.0	-6.0
80kHz	-9.0	-9.0
107kHz	-12.0	-11.9
195kHz	-18.0	-17.9



